

CLAIMS

What is claimed is:

- 1 1. A method comprising the steps of:
 - 2 a) receiving an outgoing audio signal; and
 - 3 b) coupling the audio signal to a subscriber line through a plurality of
 - 4 transistors coupled in a common base configuration.
- 1 2. The method of claim 1 further comprising the step of:
 - 2 c) receiving linefeed driver control signals for controlling battery feed to the
 - 3 subscriber line, wherein the outgoing audio signal and the linefeed driver control signals are
 - 4 received on the same signal lines.
- 1 3. The method of claim 1 wherein the plurality of transistors comprises bipolar
- 2 junction transistors.
- 1 4. The method of claim 1 wherein the plurality of transistors comprises field effect
- 2 transistors, wherein the common base configuration is a common gate configuration.
- 1 5. A method comprising the steps of:
 - 2 a) receiving linefeed driver control signals and outgoing audio signals on a
 - 3 same plurality of signal lines; and

4 b) providing the outgoing audio signals to a subscriber line through a common
5 base isolation stage.

1 6. The method of claim 5 further comprising the step of:

2 b) controlling a battery feed to a tip node and a ring node of the subscriber
3 line in accordance with the linefeed driver control signals.

1 7. The method of claim 5 wherein the common base isolation stage comprises a
2 plurality of bipolar junction transistors coupled in a common base configuration.

1 8. The method of claim 5 wherein the common base isolation stage comprises a
2 plurality of field effect transistors coupled in a common gate configuration.

1 9. A subscriber line interface circuit apparatus, comprising:
2 a first circuit for coupling a received outgoing audio signal to a subscriber line,
3 wherein the first circuit couples the received outgoing audio signal to the subscriber line
4 through a common base isolation stage.

1 10. The apparatus of claim 9 wherein the first circuit comprises a plurality of bipolar
2 junction transistors coupled in a common base configuration.

1 11. The apparatus of claim 9, wherein the first circuit comprises a plurality of field
2 effect transistors coupled in a common gate configuration.

1 12. The apparatus of claim 9 wherein the first circuit comprises:
2 a tip control circuit, wherein the tip control circuit increases a tip node voltage in
3 response to a first tip control signal, wherein the tip control circuit decreases a tip node
4 voltage in response to a second tip control signal; and
5 a ring control circuit wherein the ring control circuit increases a ring node voltage in
6 response to a first ring control signal, wherein the ring control circuit decreases a ring node
7 voltage in response to a second ring control signal.

1 13. The linefeed driver of claim 12 wherein the tip control circuit comprises:
2 a first transistor of a first type having an emitter coupled to receive the first tip
3 control signal;
4 a second transistor of the first type having an emitter coupled to receive the
5 second tip control signal, wherein a base of each of the first and second transistors is
6 coupled to a first node as a signal ground;
7 a third transistor of a second type having a collector coupled to a collector of the
8 first transistor and an emitter coupled to a second node;
9 a resistor having a first end coupled to the second node, a second end of the
10 resistor coupled to a base of the third transistor and a collector of the second transistor.

1 14. The subscriber line linefeed driver of claim 13 wherein the first type is a PNP
2 bipolar junction transistor, wherein the second type is an NPN bipolar junction
3 transistor.

1 15. A subscriber line interface circuit apparatus, comprising:
2 a signal processor providing an outgoing audio signal; and
3 a linefeed driver coupled to receive the outgoing audio signal, wherein the linefeed
4 driver couples the received outgoing audio signal to a subscriber line through a common
5 base isolation stage.

1 16. The apparatus of claim 15 wherein the common base isolation stage comprises a
2 plurality of bipolar junction transistors coupled in a common base configuration.

1 17. The apparatus of claim 15 wherein the common base isolation stage comprises a
2 plurality of field effect transistors coupled in a common gate configuration.

1 18. The linefeed driver of claim 15 wherein the linefeed driver comprises:
2 a tip control circuit, wherein the tip control circuit increases a tip node voltage in
3 response to a first tip control signal, wherein the tip control circuit decreases a tip node
4 voltage in response to a second tip control signal; and
5 a ring control circuit wherein the ring control circuit increases a ring node voltage in
6 response to a first ring control signal, wherein the ring control circuit decreases a ring node

7 voltage in response to a second ring control signal, wherein the signal processor provides
8 the first and second tip control signals and the first and second ring control signals.

1 19. The linefeed driver of claim 18 wherein the tip control circuit comprises:

2 a first transistor of a first type having an emitter coupled to receive the first tip
3 control signal;

4 a second transistor of the first type having an emitter coupled to receive the
5 second tip control signal, wherein a base of each of the first and second transistors is
6 coupled to a first node as a signal ground;

7 a third transistor of a second type having a collector coupled to a collector of the
8 first transistor and an emitter coupled to a second node; and

9 a resistor having a first end coupled to the second node, a second end of the
10 resistor coupled to a base of the third transistor and a collector of the second transistor.

1 20. The linefeed driver of claim 19 wherein the first type is a PNP bipolar junction
2 transistor, wherein the second type is an NPN bipolar junction transistor.